

Loncin LC1800 Genset 1000 Watt (Generator Set)



Informasi Produk

| | |
|-------------|----------------------------------|
| Kode | PX013 |
| Nama | Genset 1000 Watt (Generator Set) |
| Merk | Loncin |
| Tipe | LC1800 |
| Berat Kirim | 34 kg |

Loncin LC1800 Genset 1000 Watt (Generator Set)

Spesifikasi Produk

| | |
|------------------------------|--------------------|
| Ac Output Rata-Rata | 700 Watt |
| Ac Output Maksimum | 1000 Watt |
| Voltase Output | 220 V |
| Pengatur Tegangan | Avr |
| Start Mesin | Recoil |
| Konsumsi Bahan Bakar Per Jam | 0.3 L/Jam |
| Kanopi Genset | Open |
| Power Factor | 1 |
| Tingkat Kebisingan | 65 dB |
| Lama Pengoperasian (Rated) | 7 Jam |
| Merk Mesin Serbaguna | Loncin |
| Model Mesin Serbaguna | LC 152F |
| Kapasitas Mesin | 97 cc |
| Rpm Mesin | 3600 RPM |
| Langkah Mesin | 4 Langkah |
| Jumlah Silinder | Mesin 1 |
| Frekuensi | 50 Hz |
| Kapasitas Tanki Bahan Bakar | 4.5 L |
| Kapasitas Oli | 0.45 L |
| Dimensi (Pxlxt) | 464 x 340 x 480 mm |
| Garansi | 18 Bulan |